

SSCS520S40N1

SSCS520S40N1

Schottky Barrier Diode

- Features
 - ♦ Small surface mounting type
 - ♦ Low reverse current and low forward voltage
 - ♦ High reliability






DFN1006-2L (Bottom View)



Circuit Diagram



Applications

- ♦ High speed switching for detection
- ✤ For portable equipment:(i.e. Mobile phone, MP3, MD,

CD-ROM, DVD-ROM, Note book PC, etc.)

• Absolute maximum rating ($T_A=25^{\circ}$ unless otherwise noted)

| Parameter | Symbol | Value | Unit |
|--|------------------|------------|------|
| Repetitive Peak Reverse Voltage | Vrrm | 40 | V |
| Reverse Voltage (DC) | VR | 40 | |
| Average Rectified Forward Current | lo | 200 | mA |
| Non-Repetitive Peak Forward Surge Current@ t=8.3ms | IFSM | 1 | А |
| Operating Temperature | TJ | 150 | °C |
| Storage Temperature | T _{STG} | -40 ~ +150 | °C |


• Electrical Characteristics (T_A=25°C unless otherwise noted)

| Parameter | Symbol | Conditions | Min. | Тур. | Max. | Unit |
|----------------------------------|----------------------|------------------------|------|------|------|------|
| Reverse Voltage | VR | I _R = 100μΑ | 40 | | | V |
| Earward Valtage | VF | I _F = 100mA | | 0.42 | 0.48 | V |
| Forward Voltage | VF | I _F = 200mA | | 0.50 | 0.59 | V |
| Reverse Current I _R – | V _R = 25V | | | 1 | | |
| | IR | V _R = 30V | | | 2 | μA |



SSCS520S40N1

• Typical Performance Characteristics (T_A=25°C unless otherwise noted)



Forward Voltage vs. Forward Current

Reverse Voltage vs. Reverse Current



Package Information


Ordering Information

| Device | Package | Marking | Qty per Reel | Reel Size |
|--------------|------------|---------|--------------|-----------|
| SSCS520S40N1 | DFN1006-2L | D2 | 10000 | 7 Inch |

Mechanical Data


Case: DFN1006-2L

Case Material: Molded Plastic. UL Flammability



| DIM | Millimeters | | |
|-----|-------------|------|--|
| DIN | Min | Max | |
| Α | 0.45 | 0.55 | |
| A1 | 0.00 | 0.05 | |
| D | 0.55 | 0.65 | |
| Е | 0.95 | 1.05 | |
| b | 0.45 | 0.60 | |
| е | 0.65TYP | | |
| L | 0.2 | 0.3 | |
| L1 | 0.05REF | | |

Recommended Pad outline







DISCLAIMER

AFSEMI RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. AFSEMI DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICIENCE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

THE GRAPHS PROVIDED IN THIS DOCUMENT ARE STATISTICAL SUMMARIES BASED ON A LIMITED NUMBER OF SAMPLES AND ARE PROVIDED FOR INFORMATIONAL PURPOSE ONLY. THE PERFORMANCE CHARACTERISTICS LISTED IN THEM ARE NOT TESTED OR GUARANTEED. IN SOME GRAPHS, THE DATA PRESENTED MAY BE OUTSIDE THE SPECIFIED OPERATING RANGE (E.G. OUTSIDE SPECIFIED POWER SUPPLY RANGE) AND THEREFORE OUTSIDE THE WARRANTED RANGE.

OUR PRODUCT SPECIFICATIONS ARE ONLY VALID IF OBTAINED THROUGH THE COMPANY'S OFFICIAL WEBSITE, CRM SYSTEM, OR OUR SALES PERSONNEL CHANNELS. IF CHANGES OR SPECIAL VERSIONS ARE INVOLVED, THEY MUST BE STAMPED WITH A QUALITY SEAL AND MARKED WITH A SPECIAL VERSION NUMBER TO BE VALID.